



The SSt-6000-V is the latest in Teknic's line of DSP-based servo drives. This unit improves on its predecessor's ability as a high-bandwidth, fully digital, DSP-based amplifier that accepts $\pm 10V$ analog torque or velocity commands. Upgrading a conventional "dumb" amplifier to an SSt-6000-V will improve tracking, smoothness and settling time.

In velocity mode, the drive utilizes a proprietary servo algorithm that delivers microsecond level response to velocity errors to permit precise motor control. Moreover, this algorithm helps the drive to distinguish between motor feedback quantization error and real velocity error to eliminate self-generating velocity error.

In addition to a unique servo algorithm, the drive removes a little-known flaw present in other amps to further optimize motor performance. All other amplifiers servo control current, not torque. So servo systems that use other amplifiers actually run *open-loop* with respect to torque!

Servo controlling torque requires synchronized control of all motor phases with respect to the magnetic field of the motor's rotor. Conventional amps control each motor phase with a separate, dissociated current loop servo. This scheme ignores the fact that the motor phases are tied together and thus interdependent. Furthermore, small errors in each phase can combine to create a large vector (torque) error. These torque errors lead to inadvertent velocity errors.

The SSt-6000-V employs a proprietary torque control method: *sinewave, vector feed-forward with DQ decoupling*. This method constantly measures all the variables required to accurately calculate the true torque output (and the out-of-phase currents which only heat the motor) and continuously works to servo the torque to the commanded value and the out-of-phase currents to zero. So in the SSt, the torque is truly under closed-loop control. This actively removes errors in motor torque and preempts the resulting velocity error.

So with the same servo controller, OEMs will see smoother motion and tighter velocity control by simply replacing their velocity amplifiers with SSt-6000-V drives.



ROBUST PERFORMANCE

Outstanding Large-Signal Bandwidth

Most amplifier vendors specify small-signal bandwidth. However, in the real world, to effectively fight disturbances, accurately track aggressive commands, and settle loads quickly, amps must respond rapidly to *large-signal* inputs. This is where the SSt-6000-V's torque control method has a clear advantage. For example, at the moment a motor begins to change from acceleration to deceleration, it requires a large-signal change in torque. At 75% of rated motor speed, the torque response time disparity between an SSt and a conventional digital, sinewave amp is striking: 0.1ms vs. 10ms!¹ This difference has a significant impact on smoothness, tracking and settling time.

Anti-Resonance Torque Loops

The digital torque loop can be tuned to control unwanted resonances. This provides optimal performance with axes that suffer from in-band resonances.

FLEXIBLE, LOW EFFORT INTEGRATION

Drop-in Controller Compatibility

SSt drives have an open control interface, accepting a standard $\pm 10V$ analog torque or velocity command.

Universal Motor Interface

The SSt controls rotary and linear servomotors, brush motors, galvos, voice coils, etc. from any manufacturer with virtually no motor restrictions (such as minimum inductance value).

Ease of Development/Assembly Features

- The robust, proprietary torque compensator provides perfect tuning repeatability via a simple file download.
- The SSt-6000-V provides intuitive diagnostics to qualify production machines and troubleshoot systems rapidly.
- QuietDesign™ EMI reduction system eliminates shield clamps, ferrite slugs, etc. required to meet CE.
- Built-in monitoring detects faulty cables and sensors.
- OEM friendly cabling is robust, mass producible and easily testable. With CAD drawings available at no charge, the cabling is economical to build.

¹ Test conditions: 8 pole motor; $K_t=11.1$ oz-in/A; $R=0.76\Omega$; $L=1.25mH$; Torque Command = $\pm 18A$ square wave; 20 oz-in² load; SSt-1500-T vs. digital sinewave amp with equivalent power ratings.

ADDITIONAL CAPABILITIES...

Software Scope

Now engineers and technicians can view, configure and troubleshoot the entire motion system using nothing but QuickSet software. A built-in oscilloscope enables quick troubleshooting by providing detailed information about servo drive performance. Advanced triggering modes allow you to capture data related to the start or finish of a move or even a safety shutdown event. View any monitor port variable (commanded torque, actual torque, etc.) alongside specific move status (idle, move active, etc.) or drive status (shutdowns, limits, saturation, etc.). This easy-to-use tool provides an effective method for system evaluation, configuration and diagnosis.

Shutdown History

Quickly discover the root cause of machine problems: A historical view of recent fault activity is captured which allows engineers and technicians to retrace a series of safety shutdowns in a machine.

Extremely Fast Torque Response Time

Sinewave commutation with vector feed-forward and DQ decoupling provides near-zero torque response time *at any speed*.

Elimination of Motor Burn-out
Motor burn-out is eliminated using true RMS limiting and no added wiring or sensors. It is much faster and more effective than I²t or thermostats.

SmartSaturation™

This dynamic algorithm maintains elegant motor control in the event of voltage and/or current saturation.

Multiple Power Inputs

Dual input power connectors allow for daisy chain simplicity.

Auto-Calibrating Sensors

The current sensors are continuously monitored and recalibrated to ensure precise and repeatable performance as power usage and temperatures fluctuate.

Exceptional Noise immunity

The drive fully isolates logic and power, making it highly noise immune. This allows OEMs to avoid the hassle and cost of single point grounding, star power wiring, inductive control, etc. typically required in ±10V systems.

SPECIFICATIONS		
GENERAL	Dimensions, in (mm):	8.93 (227) x 5.56 (141) x 3.15 (80).
	Weight, oz (g):	71 (2015).
ENVIRONMENTAL	Temperature:	0-40 Degrees C.
	Humidity:	0-95%, non-condensing.
COMPLIANCE	Electrical safety:	EN 61010, UL508C.
	EMI:	EN 50081-2, EN 50082-2.
	Machine safety:	EN 954-1, with proper power control.
OUTPUT POWER	Current:	23 Amps Peak (3 seconds). 9 Amps RMS vertical on metal surface. 12 Amps RMS with mounted fan cooling.
	PWM ripple frequency:	28kHz, center balance vector type.
COMPENSATOR	Torque control:	Synchronous vector torque control with DQ decoupling, and automatic current sensor calibration, tunable response for resonance control, ongoing vector refinement.
ENCODER	Interface:	Single-ended or differential, user selectable.
	Max count rate:	15MHz.
	Features:	Bad sequence detection, digital filtering.
MOTOR COMPATIBILITY	Requirements:	Any permanent magnet motor of any type.
± 10V ANALOG INPUT	Format:	Differential input, ±10V range.
	Impedance:	>10kΩ.
	Range:	10% of peak per volt.
LIMIT INPUTS	Interface:	TTL with 1kΩ pull-up, digitally filtered.
HALL SENSOR INPUTS	Specifications:	Optically isolated; 1kΩ pull-up to +5V.
	Features:	Digitally filtered; used for setting torque vector upon initialization; drive can run in hall-less mode.
DEDICATED INTERFACE INPUTS/OUTPUTS	Outputs:	Drive ready; encoder and limits pass-through, +5V.
	Inputs:	Enable power stage; Analog torque, Analog velocity; encoder; limits.
	Format:	0.5V-4.5V analog signal (0=2.5V).
REAL-TIME MONITOR PORT	Features:	Configurable filtering, sync pulse at move start, wide scaling with high zoom, non-volatile configuration.
	Output variables:	Commanded torque, actual torque, actual velocity, max phase voltage.
PROTECTION & SAFETY FUNCTIONS	Drive protection:	Short circuit (phase-to-phase, phase-to-ground), over temp, over voltage, over current, protected for open windings, fused.
	Motor protection:	True RMS torque limiting, automatic speed limit, motor jam detection, over temp.
	Mechanical safeguards:	Limit switch servoing, adjustable torque limit and adjustable speed limit, encoder bad sequence detection, encoder run-away protection.
INPUT SUPPLY	Input voltage:	90-240 VAC (50-60Hz) or 128-340 VDC.
COUNTRY OF ORIGIN	Manufactured in:	USA.